



# JB101U


## Quick Reference Guide

[www.freetekic.com](http://www.freetekic.com)

**Jabees JB101U is a Bluetooth® Mono Headset supports Multipoint.**

### Overview of JB101U:

- (1) Earhook
- (2) Charging jack
- (3) On/off / MF Button
- (4) LED
- (5) Speaker
- (6) Microphone



### CHARGING THE BATTERY

1. Plug the AC charger into the headset.
2. Plug the other end of the AC charger into your wall power socket.
3. The red indicator on the headset will be on.
4. When the battery is fully charged, the red indicator will turn off and the blue indicator will turn on.

#### Important

- For first time use, please charge the headset fully before using.

### MULTIFUNCTIONAL BUTTON

Power on/off, Pairing, Answer / End / Reject / Transfer calls, Voice dialing, Redial, Language selection.

### TURNING HEADSET ON / OFF

#### To turn the headset on:

Press and hold the MF-button for 5 seconds. The blue indicator of the headset flashes 3 times. The headset is now turned on.

#### To turn the headset off:

Press and hold the MF-button for 5 seconds. The blue indicator of the headset flashes 2 times. The headset is now turned off.

### PAIRING THE HEADSET

You are required to pair the headset with your mobile phone once before using it.

1. Press and hold the MF-button for 5 seconds until indicator light turns in solid blue to go into the pairing mode.
2. Activate Bluetooth® on your mobile phone.
3. Set your phone to discover 'JB101U' and follow the instruction.
4. If your phone asks for passkey or PIN-code, confirm with 0000.
5. Your JB101U will confirm when pairing is completed by showing a blue indicator light flashes two times once every 5 seconds.

#### Note:

1. If JB101U headset is not in pairing mode, your mobile phone won't find the headset. Please set the headset into pairing mode before making your mobile phone search for JB101U.

2. If no pairing is possible for a period of time (approximately 5 minutes), the headset will automatically leave pairing mode and turn off. If headset haven't connected with any devices and there is no more action for a period of time (approximately 15-20 minutes), the headset will be automatically off. You may need to start all over again.

### PAIRING THE HEADSET WITH THE SECOND MOBILE PHONE

JB101U supports multipoint. This means JB101U can be paired and connected with 2 mobile phones at the same time.

1. Pair and connect the headset with the first mobile phone.  
(Please refer to the 'PAIRING THE HEADSET'.)
2. Turn off the headset.
3. Press and hold the MF-button to go to the pairing mode and connect with second mobile phone.
4. Turn off the headset after connecting with second mobile phone.
5. Turn on the headset, two mobile phones will connect with JB101U at the same time.

### LANGUAGE SELECTION

Turn on the JB101U after factory reset is successful, the headset will go into the language menu and then you will hear voice prompt in 3 languages, you can press the MF button to select your preferred language accordingly.

### MAKING CALLS

Once the headset is successfully paired with your mobile phone, you can use it to make and receive calls. The headset can be used with voice dialing if your mobile phone supports this feature. Please consult your mobile phone's manual for more information.

#### 1. Using voice dialing:

Short press the MF-button, wait for a voice prompt and say the name of the person you want to call.

#### 2. Using the phone keys to make a call:

Enter and dial the number on the mobile phone as you normally do. Once the call has been set up, the sound will be transmitted to your headset automatically.

#### 3. Redial:

Press and hold the MF-button for 2 seconds to redial the last number you called.

### ANSWERING / ENDING /REJECTING CALLS

When the headset is turned on and there is an incoming call, you will hear a musical tone.

- Press the MF-button to answer the call.
- Press the MF-button to end the call.
- Press and hold MF-button for 2 seconds to reject the call.

### PUT THE CALL ON HOLD

#### In call state:

Press and hold the MF-button for 2 seconds to put the active call on hold.

#### In call wait state:

Press and hold the MF-button for 2 seconds to put the current call on hold and accept the call waiting.

Press the MF-button once to end the call waiting.

### TRANSFERRING CALLS

#### To transfer a call to the mobile phone and back:

During both incoming call and outgoing call state, you can press & hold the MF-button for

3 seconds to transfer the call to the mobile phone. If you want to transfer the call back to the headset, Press the MF-button for 3 seconds. Some mobile phones may require more confirmation.

### ADJUST THE VOLUME

You can increase/decrease the volume by increasing/decreasing the volume of your mobile phone. The volume of your headset will be adjusted automatically. Please consult your mobile phone's manual for more information.

### WHEN THE BATTERY IS LOW

If the voice prompt says 'battery is low', you need to charge the headset.

### CONNECTING WITH A PC OR PDA

You are allowed to connect the headset with a Bluetooth® enabled PC or PDA that is supported with headset and/or handsfree profiles. Please refer to the user manual of your Bluetooth® enabled PC or PDA for setup information.

### FACTORY RESET

To factory reset the headset, you will have to turn on the headset and go into the pairing mode. Under this mode, press and hold MF-button for 3 seconds until hearing "beep" and "beep, beep", loose MF-button immediately, then, the indicator light remains in solid blue for 5 seconds and then turns off. Now, the factory reset is successful. The headset will go into language selection mode automatically when it is turned on again. (Please refer to the above 'Language selection' instruction.).

### GUARANTEE

Jabees is a registered trademark of FreeTek International Co.,Ltd. Other brands and product names are trademarks of their respective owners. Jabees warrants this product against all defects in material and workmanship for a period of **twelve (12) months** from the date of original purchase of the product. The conditions of this guarantee and the extent of responsibility of Jabees under this guarantee can be read in the Warranty Card.